

# ROP-401/EU

The **ROP-400** call point for outdoor applications is used to manually trigger an alarm when a fire is discovered. It is designed to operate in the detection line of the **ACSP-402**; addressable fire alarm control panel.

- resettable plastic pane
- **ROP-KEY-U** key (sold in set) to enable:
  - testing
  - resetting
- LED indicator/li>
- double-sided short-circuit isolator
- power supply from the detection line
- mounting box included
- optional protective cover to prevent unintentional activation – **ROP-FLAP**

Operating temperature range	-25°C...+70°C
Weight	180 g
Maximum humidity	95%
Current draw when detecting	170 µA
Current draw when emitting an alarm	450 µA
IP rating	IP66
Power supply voltage	18...26 V DC
Dimensions without holders	87 x 87 x 53 mm
Dimensions with holders	117 x 87 x 53 mm