

CA-64 E

ZONE EXPANSION MODULE

The zone expansion modules for INTEGRA and VERSA control panels make it possible to increase the number of available zones for connecting burglar detectors and automation devices. Owing to the pulse analysis function, these expanders can be used for direct connection of vibration and roller shutter detectors.

FEATURES

- system expansion with 8 zones
- support for NO, NC, EOL, 2EOL/NO, 2EOL/NC zone configurations
- programmable EOL resistance value
- pulse analysis with sensitivity setting for vibration and rollerblind sensors
- supported also by the **VERSA** alarm control panels



TECHNICAL SPECIFICATION

Supply voltage	12 V DC $\pm 15\%$
Number of programmable zones	8
Current consumption, standby	70 mA
Current consumption, maximum	70 mA
Dimensions of electronics board	57 x 80 mm
Environmental class according to EN50130-5	II
Operating temperature range	-10°C...+55°C
Weight	47 g