

# INT-R

## MULTIFUNCTION EXPANDER FOR CARD / CHIP READERS

Extension module for INTEGRA control panels enabling proximity card readers and/or iButton chip readers to be connected to implement access control to and arming/disarming of the partition. The INT-R expander can interface with the INTEGRA and CA-64 alarm control panels.

### FEATURES

- support for two proximity card / iButton chip readers
- compatible with Wiegand 26 format readers
- relay to control electromagnetic door lock
- input for door status control
- input for door opening with a button
- capability to automatically open the door in case of fire alarm
- tamper input



### TECHNICAL SPECIFICATION

Supply voltage	12 V DC $\pm$ 15%
Standby current consumption	110 mA
Maximum current consumption	150 mA
Relay contacts rating (resistive load)	5 A / 30 V DC
Environmental class	II
Operating temperature range	-10°C...+55°C
Maximum humidity	93 $\pm$ 3%
Dimensions	140 x 68 mm
Weight	80 g